

# VISION NETWORK REPEATER

## Addressable Fire Alarm Control Panel Repeater

### Features

- ▶ Automatic display brightness adjustment
- ▶ Silenceable internal sounder
- ▶ Low current, 24 VDC powered
- ▶ Slim compact construction
- ▶ Configurable functionality
- ▶ Configurable languages
- ▶ Robust, full colour, 7" 800 x 480 touch screen graphical display
- ▶ Full indication of all information displayed at the Fire Control Panel
- ▶ Connection via RS485 Control Panel Network
- ▶ 24 programmable function buttons, Selectable based on user account permissions



### Description

The Latitude Vision Network Repeater allows a full display and optional control of the Latitude fire alarm control panel from a small and unobtrusive local control station.

Latitude repeaters can be configured to offer full display and control to replicate the functionality of the fire control panel or to operate as a simple, display only device for applications where access to control the fire alarm system would be inappropriate.

For other annunciation and control applications, Latitude can be configured to provide customisable switches and indications for a host of fire system ancillary functions.

Available in several standard formats, Vision Repeater can be mounted directly onto a wall, be recessed using our quick-fix adaptor frame or fully flush mounted.

### Specification

<b>Size</b>	235mm (L) x 170mm (H) x 55mm (D)
<b>Construction</b>	1.2mm mild sheet steel
<b>IP Rating</b>	IP 30
<b>Finish</b>	Epoxy powder coated
<b>Colour - Lid &amp; Box</b>	BS 00 A 05 fine texture
<b>Weight</b>	2 kg
<b>Display</b>	Full colour 800 x 480 LCD with resistive touch screen and automatic backlight dimming
<b>Cable entry</b>	3 knockouts top, 3 knockouts back
<b>24V supply</b>	21 to 30 VDC
<b>RS 485 fire panel network</b>	Up to 127 panel nodes



For further information visit our [website](#).  
Hochiki reserves the right to alter the specification of its products from time to time without notice. Although every effort has been made to ensure the accuracy of the information contained in this document it is not warranted or represented by Hochiki to be a complete and up-to-date description. Check online for current version.